

Measuring instrument - EEM-SB370-C



1158951

<https://www.phoenixcontact.com/pc/products/1158951>

Please be informed that the data shown in this PDF document is generated from our Online Catalog. Please find the complete data in the user documentation. Our General Terms of Use for Downloads are valid.



Multi-functional energy measuring device without display, with integrated Ethernet and cloud interface for measuring electrical parameters in low-voltage installations up to 690 V.

Measuring instrument - EEM-SB370-C



1158951

<https://www.phoenixcontact.com/pc/products/1158951>

Commercial Data

Item number	1158951
Packing unit	1 pc
Minimum order quantity	1 pc
Product Key	CK4C21
GTIN	4063151166410
Weight per Piece (including packing)	457 g
Weight per Piece (excluding packing)	447 g
Customs tariff number	90303100
Country of origin	DE

Technical Data

Product properties

Product type	Energy meter
--------------	--------------

Insulation characteristics

Overvoltage category	III (300 V)
Pollution degree	2

Electrical properties

Electrical isolation	IEC 61010-1 (Overvoltage category III at 300 V AC Overvoltage category II at 600 V AC)
	IEC 61010-1 (Overvoltage category III at 300 V AC Overvoltage category II at 600 V AC)
	IEC 61010-1 (Measurement category III at 300 V AC Measurement category II at 600 V AC)
Test voltage	4 kV AC (50 Hz, 1 min.)
Maximum power dissipation for nominal condition	10 VA
Mains type	3-phase (3 or 4-conductor), 2-phase (2-conductor), and single-phase (1-conductor)

Supply

Supply voltage range	100 V AC ... 230 V AC ($\pm 20\%$)
	150 V DC ... 250 V DC ($\pm 20\%$)
Power consumption	≤ 4 W
Nominal frequency	50 Hz ... 60 Hz (AC sine)

Input data

Measuring principle	True r.m.s. value measurement
Measured value	AC sine (50/60 Hz)
Acquisition of harmonics	up to 63rd harmonic
Description of the input	Digital input in accordance with IEC/EN 61131-2 (type 3)
Number	1
Voltage input signal	24 V DC
Voltage input signal	0 V DC ... 30 V DC
Current input signal	2 mA ... 15 mA
Protection	250 mA (fast-blow)

Measurement: Voltage

Input name	Voltage measuring input V1, V2, V3
Input voltage range direct	35 V AC ... 690 V AC (Phase/Phase)
	20 V AC ... 400 V AC (0)
Input voltage range via external transformers	60 V AC ... 2000000 V AC (primary)
	60 V AC ... 400 V AC (secondary)
Surge voltage capacity	760 V AC (Phase/Phase)
Precision	0.2 %

Measuring instrument - EEM-SB370-C



1158951

<https://www.phoenixcontact.com/pc/products/1158951>

Power consumption	< 2 VA
-------------------	--------

Measurement: Current

Input name	Current measurement I1, I2, I3
Input current	1 A (secondary)
	5 A (secondary)
Current measuring range	1 A ... 20000 A (primary)
Overload capacity	6 A (I_{max})
Response threshold from measuring range nominal value	10 mA (1 A)
	50 mA (5 A)
Precision	0.2 %
Current overload	50 A for 1 s
Power consumption	< 0.5 VA

Measurement: Power

Precision	0.5 %
Active energy (IEC 62053-22)	Class 0.5 S
Reactive power (IEC 62053-23)	Class 2
ANSI C12.20	Class 0.5 S

Output data

Output description	Digital output in accordance with IEC/EN 61131-2 (type 3)
Number	1
Current output signal	≤ 100 mA
Voltage output signal	24 V DC
Protection	250 mA (fast-blow)

Connection data

Current / voltage / supply

Connection method	Screw connection
Stripping length	8 mm
Screw thread	M3
Conductor cross section solid	0.2 mm ² ... 6 mm ²
Conductor cross section flexible	0.2 mm ² ... 4 mm ²
Conductor cross section AWG	24 ... 10
Torque	0.5 Nm ... 0.6 Nm

Current / voltage / supply

Connection method	Screw connection
Stripping length	7 mm
Screw thread	M3
Conductor cross section solid	0.14 mm ² ... 2.5 mm ²
Conductor cross section flexible	0.14 mm ² ... 1.5 mm ²
Conductor cross section AWG	26 ... 14
Torque	0.5 Nm ... 0.6 Nm

Measuring instrument - EEM-SB370-C



1158951

<https://www.phoenixcontact.com/pc/products/1158951>

Interfaces

Data: Network interface

Communication protocol	Modbus/TCP
	REST
Connection method	RJ45

Data: Network interface

Communication protocol	MQTT
Connection method	RJ45
Number of connections	2

IoT capabilities

Platform: PROFICLOUD

Supports cloud computing	yes
Protocol / IP-Port	HTTPS / 443
	MQTT / 8883
Smart Services	Device Management Service
	Time Series Data Service

Dimensions

Width	90 mm
Height	80 mm
Depth	82 mm

Environmental and real-life conditions

Ambient conditions

Degree of protection	IP20 (Housing)
Ambient temperature (operation)	-10 °C ... 55 °C
Ambient temperature (storage/transport)	-40 °C ... 70 °C
Altitude	≤ 2000 m
Max. permissible relative humidity (operation)	≤ 95 % (non-condensing)

Approval data

CE

Certificate	CE-compliant
-------------	--------------

CE

Certificate	UKCA-compliant
-------------	----------------

CE

Identification	UL/C-UL Listed UL 61010-1
----------------	---------------------------

UL data

Operating mode	Indoor use
----------------	------------

Measuring instrument - EEM-SB370-C



1158951

<https://www.phoenixcontact.com/pc/products/1158951>

UL data

Operating mode	Indoor use
----------------	------------

Mounting

Mounting type	DIN rail mounting
Mounting position	Horizontal DIN rail


Measuring instrument - EEM-SB370-C




1158951

<https://www.phoenixcontact.com/pc/products/1158951>

Approvals

 **UL Listed**
Approval ID: FILE E 357804

 **cUL Listed**
Approval ID: FILE E 357804

cULus Listed

Measuring instrument - EEM-SB370-C



1158951

<https://www.phoenixcontact.com/pc/products/1158951>

Classifications

ECLASS

ECLASS-9.0	27142330
ECLASS-10.0.1	27142330
ECLASS-11.0	27142330

ETIM

ETIM 8.0	EC002301
----------	----------

UNSPSC

UNSPSC 21.0	41113600
-------------	----------

Measuring instrument - EEM-SB370-C



1158951

<https://www.phoenixcontact.com/pc/products/1158951>

Environmental Product Compliance

REACH SVHC

Lead 7439-92-1

1158951

<https://www.phoenixcontact.com/pc/products/1158951>

Accessories

Current transformer

Current transformer - PACT MCR-V1-21-44 - 2277268

<https://www.phoenixcontact.com/pc/products/2277268>



Bus-bar current transformer, primary current can be selected between 50...500 A AC; secondary current can be selected as 1 A AC or 5 A AC; accuracy class can be selected as 0.5 or 1; rated power can be selected

Current transformer

Current transformer - PACT MCR-V2- 3015- 60 - 2277271

<https://www.phoenixcontact.com/pc/products/2277271>



Window-type current transformer, primary current can be selected between 50...750 A AC; secondary current can be selected as 1 A AC or 5 A AC; accuracy class can be selected as 0.5 or 1; rated power can be selected

1158951

<https://www.phoenixcontact.com/pc/products/1158951>

Current transformer

Current transformer - PACT MCR-V2- 4012- 70 - 2277284

<https://www.phoenixcontact.com/pc/products/2277284>



Window-type current transformer, primary current can be selected between 75... 1000 A AC; secondary current can be selected as 1 A AC or 5 A AC; accuracy class can be selected as 0.5 or 1; rated power can be selected

Current transformer

Current transformer - PACT MCR-V2- 5012- 85 - 2277297

<https://www.phoenixcontact.com/pc/products/2277297>



Window-type current transformer, primary current can be selected between 100.. .1500 A AC; secondary current can be selected as 1 A AC or 5 A AC; accuracy class can be selected as 0.5 or 1; rated power can be selected

1158951

<https://www.phoenixcontact.com/pc/products/1158951>

Current transformer

Current transformer - PACT MCR-V2- 6015- 85 - 2277336

<https://www.phoenixcontact.com/pc/products/2277336>



Window-type current transformer, primary current can be selected between 200 . . . 1,250 A AC; secondary current can be selected as 1 A AC or 5 A AC; accuracy class can be selected as 0.5 or 1; rated power can be selected

Current transformer

Current transformer - PACT MCR-V2-10020-129 - 2277378

<https://www.phoenixcontact.com/pc/products/2277378>



Window-type current transformer, primary current can be selected between 800 and 4,000 A AC, secondary current can be selected 1 A AC or 5 A AC, accuracy class can be selected 0.5 or 1, rated power can be selected

1158951

<https://www.phoenixcontact.com/pc/products/1158951>

Current transformer

Current transformer - PACT MCR-V3-60 - 2277417

<https://www.phoenixcontact.com/pc/products/2277417>



Winding current transformer, primary current can be selected between 1...40 A AC; secondary current can be selected as 1 A AC or 5 A AC; accuracy class can be selected as 0.5 or 1; rated power can be selected

Current transformer

Current transformer - PACT MCR-V2-3015-60-PT - 2907413

<https://www.phoenixcontact.com/pc/products/2907413>



Window-type current transformer with screw and Push-in connection technology, conductor connection for Push-in: from directly above, no tools required. The following can be selected: primary current (50 ... 750) A AC, secondary current (1 or 5) A AC, accuracy class 0.5 or 1, VA power

Measuring instrument - EEM-SB370-C

1158951

<https://www.phoenixcontact.com/pc/products/1158951>

Current transformer

Current transformer - PACT MCR-V2-4012-70-PT - 2907414

<https://www.phoenixcontact.com/pc/products/2907414>



Window-type current transformer with screw and Push-in connection technology, conductor connection for Push-in: from directly above, no tools required. The following can be selected: primary current (100 ... 1000) A AC, secondary current (1 or 5) A AC, accuracy class 0.5 or 1, VA power

Current transformer

Current transformer - PACT MCR-V2-5012-85-PT - 2907416

<https://www.phoenixcontact.com/pc/products/2907416>



Window-type current transformer with screw and Push-in connection technology, conductor connection for Push-in: from directly above, no tools required. The following can be selected: primary current (100 ... 1500) A AC, secondary current (1 or 5) A AC, accuracy class 0.5 or 1, VA power

Measuring instrument - EEM-SB370-C



1158951

<https://www.phoenixcontact.com/pc/products/1158951>

Current transformer

Current transformer - PACT MCR-V2-6015-85-PT - 2907417

<https://www.phoenixcontact.com/pc/products/2907417>



Window-type current transformer with screw and Push-in connection technology, conductor connection for Push-in: from directly above, no tools required. The following can be selected: primary current (200 ... 1600) A AC, secondary current (1 or 5) A AC, accuracy class 0.5 or 1, VA power

Phoenix Contact 2022 © - all rights reserved

<https://www.phoenixcontact.com>

PHOENIX CONTACT GmbH & Co. KG

Flachsmarktstraße 8

D-32825 Blomberg

+49 (0) 5235-3 00

info@phoenixcontact.com